

RWY Designator	APCH LGT type LEN INTST	THR LGT colour WBAR	VASIS (MEHT) PAPI	TDZ LGT LEN	RWY centre line LGT LEN, spacing colour, INTST	RWY edge LGT LEN Spacing, colour INTST	RWY end LGT colour WBAR	SWY LGT LEN (M) colour
1	2	3	4	5	6	7	8	9
24R	ALSAF LIL_LIH Sequence flash available	G LIH	3.0° 65.00 ft	W LIL_LIH	Up to 2700 m: W LIH; 2700 - 3300 m: R/W LIH; 3300 - 3600 m: R LIH. 15 m spacing	Up to 300 m R LIH; 300 m - 3000 m W LIH; 3000 m - 3600 m Y LIH; 60 m spacing	R LIH	-
06R	ALSAF LIL_LIH Sequence flash available	G LIH	3.0° 65.00 ft	W LIL_LIH	Up to 3100 m W LIH; 3100 m - 3700 m R/W LIH; 3700 m - 4000 m R LIH; 15 m spacing.	Up to 3400 m W LIH; 3400 m - 4000 m Y LIH; 60 m spacing	R LIH	-
24L	ALSAF LIL_LIH Sequence flash available	G LIH	3.0° 65.00 ft	W LIL_LIH	Up to 3100 m W LIH; 3100 m - 3700 m R/W LIH; 3700 m - 4000 m R LIH; 15 m spacing.	Up to 3400 m W LIH; 3400 m - 4000 m Y LIH; 60 m spacing	R LIH	-

Remarks	
10	
06L	LED lights used in the full length of runway centre line and edge lights. Incandescent lights are used in the first 600 m of the approach lighting system; remaining length LED lights are used. LED lights are used for the full length of the sequence flash lights.
24R	LED lights used in the full length of runway centre line and edge lights. Incandescent lights are used in the first 600 m of the approach lighting system; remaining length LED lights are used. LED lights are used for the full length of the sequence flash lights.
06R	LED lights are used for the full length of the sequence flash lights.
24L	LED lights are used for the full length of the sequence flash lights.

EDDB AD 2.15 Other lighting, secondary power supply

1	ABN/IBN location, characteristics and hours of operation	Sequence flash white/white on TWR
2	LDI location and LGT Anemometer location and LGT	See Chart AD 2 EDDB 2-5
3	TWY edge and centre line LGT	TWY edge lights of TWYs A, B, C, D, G, H, K, K1, K2, K3, K6, K5(K-G), K1(K2-N1), K5(APR3-K), K4(CATIII-RWY), K4(APR3-CATIII), L8 (CATIII-D), L5(D-F), L1(CATIII-C), L2(CATIII-C), L1(RWY-CATIII), L2(RWY-CATIII), L3(RWY-CATIII), L4(RWY-CATIII), L5(RWY-CATIII), L6(RWY-CATIII), L7(RWY-CATIII), L8(RWY-CATIII), M, M1, M2, M3, M4, M5, M6, M7, M8, M9, P1, P2, Q1, Q2, R, T, V1, V2, V3, V4, Y1: B LIL TWY Center line lights of TWYs A, B, C, D, E, F, G, K1, K2, K3, K6, K1(K2-N1), K4(CATIII-RWY), L8 (CATIII-D), L5(D-F), L1(CATIII-C), L2(CATIII-C), L3(CATIII-D), L4(CATIII-D), L5(CATIII-D), L6(CATIII-D), L7(CATIII-C), L1(RWY-CATIII), L2(RWY-CATIII), L3(RWY-CATIII), L4(RWY-CATIII), L5(RWY-CATIII), L6(RWY-CATIII), L7(RWY-CATIII), L8(RWY-CATIII), M1, M2, M3, M4, M5, M7, M8, M9, P1, P2, Q, Q1, Q2, R, T, V1, V2: G LIH
4	Secondary power supply including switch-over time	Available / 1 SEC
5	Remarks	Nil