

INITIAL CLIMB PROCEDURE RNP1 with RF functionality RWY 16R**NENIG 6W**

Path Terminator	Waypoint Name	Fly Over	Course °Mag (°T)	Magnetic Variation	Distance (NM)	Turn Direction	Altitude Constraint	Speed Limit (IAS)	Navigation Performance
CA	-	-	159° (162.6°)	3°	-	-	+410	-	RNP1
CF	RF601	-	159° (162.6°)	3°	-	-	+620	-200	RNP1
RF centre: RF620 r=2.1NM	RF604	-	-	-	2.5	R	-	-200	RNP1
TF	RF603	-	225° (228.7°)	-	2.6	-	-	-200	RNP1
RF centre: RF606 r= 2.5NM	RF609	-	-	-	3.6	R	-6000 +3000	-200	RNP1
TF	RF711	-	303° (305.9°)	-	16.7	-	-	-200	RNP1
TF	NENIG	-	278° (281.2°)	-	10.0	-	-	-	RNP1

SOSIV 6W

Path Terminator	Waypoint Name	Fly Over	Course °Mag (°T)	Magnetic Variation	Distance (NM)	Turn Direction	Altitude Constraint	Speed Limit (IAS)	Navigation Performance
CA	-	-	159° (162.6°)	3°	-	-	+410	-	RNP1
CF	RF601	-	159° (162.6°)	3°	-	-	+620	-200	RNP1
RF centre: RF620 r=2.1NM	RF604	-	-	-	2.5	R	-	-200	RNP1
TF	RF603	-	225° (228.7°)	-	2.6	-	-	-200	RNP1
RF centre: RF606 r=2.5NM	RF608	-	-	-	5.5	R	-6000 +3000	-200	RNP1
TF	RF812	-	348° (351.6°)	-	7.3	-	+5000	-200	RNP1
TF	RF707	-	353° (355.8°)	-	6.3	-	+6000	-	RNP1
TF	RF708	-	353° (355.8°)	-	7.3	-	+FL110	-	RNP1
TF	SOSIV	-	353° (355.8°)	-	6.3	-	-	-	RNP1

XENOL 6W

Path Terminator	Waypoint Name	Fly Over	Course °Mag (°T)	Magnetic Variation	Distance (NM)	Turn Direction	Altitude Constraint	Speed Limit (IAS)	Navigation Performance
CA	-	-	159° (162.6°)	3°	-	-	+410	-	RNP1
CF	RF601	-	159° (162.6°)	3°	-	-	+620	-200	RNP1
RF centre: RF620 r=2.1NM	RF604	-	-	-	2.5	R	-	-200	RNP1
TF	RF603	-	225° (228.7°)	-	2.6	-	-	-200	RNP1
RF centre: RF606 r=2.5NM	RF607	-	-	-	2.6	R	-6000 +3000	-200	RNP1
TF	RF709	-	283° (285.8°)	-	15.7	-	-	-200	RNP1
TF	XENOL	-	273° (276.4°)	-	11.0	-	-	-	RNP1

Waypoint Identifier	Coordinates
RF601	41°46'15.68"N 012°14'42.00"E
RF603	41°42'19.24"N 012°11'14.30"E
RF604	41°44'01.66"N 012°13'49.99"E
RF607	41°41'49.84"N 012°07'57.93"E
RF608	41°43'56.33"N 012°05'42.89"E
RF609	41°42'19.44"N 012°06'49.63"E
RF707	41°57'25.40"N 012°03'40.60"E
RF708	42°04'42.22"N 012°02'57.76"E
RF709	41°46'05.80"N 011°47'44.47"E
RF711	41°52'03.44"N 011°48'47.61"E
RF812	41°51'08.83"N 012°04'17.30"E
RF arc centre Identifier	Coordinates
RF620	41°45'37.91"N 012°12'01.36"E
RF606	41°44'12.00"N 012°09'02.12"E