

STANDARD DEPARTURE CHART - INSTRUMENT

RJFF / FUKUOKA

RNAV SID and TRANSITION

KURUME FIVE DEPARTURE GABAI TRANSITION / BERSA TRANSITION		RNAV 1
<p>Note 1) DME/DME/IRU or GNSS required. ※The aircraft equipped with only DME/DME/IRU must be able to update its position without delay at the starting point of take-off roll. 2) RADAR service required.</p>		<p>RWY16L/16R DGC : 14.2NM to YAMEK - 9.4NM to YAMEK IKE : 14.2NM to YAMEK - 9.4NM to YAMEK RWY34L DGC : 3.3NM to F4L01 - 1.8NM to F4L01 IKE : 3.3NM to F4L01 - 1.8NM to F4L01 F4L01 - 2.8NM to FF402 AHT : F4L01 - 2.0NM to FF403 RWY34R DGC : 3.3NM to FF401 - 1.8NM to FF401 IKE : 3.3NM to FF401 - 1.8NM to FF401 FF401 - 2.8NM to FF402 AHT : FF401 - 2.0NM to FF403</p>
DME GAP	<p>RWY16L/16R : DER - 14.2NM to YAMEK RWY34L : DER - 3.3NM to F4L01 1.8NM to F4L01 - F4L01 RWY34R : DER - 3.3NM to FF401 1.8NM to FF401 - FF401</p>	
Critical DME		Inappropriate Nav aids
Inappropriate Nav aids		See AD1.1.6.10.3. Inappropriate NAVAIDs for RNAV1
<p>VAR 8°W</p>		
<p>KURUME FIVE DEPARTURE</p> <p>RWY34R : Climb on HDG 338° at or above 500FT, direct to FF401, to FF402, to FF403, to YURRY, to YAMEK. RWY34L : Climb on HDG 338° at or above 500FT, direct to F4L01, to FF402, to FF403, to YURRY, to YAMEK. RWY16L/16R : Climb on HDG 158° at or above 500FT, direct to YAMEK.</p> <p>Note RWY34R/34L : 7.0% climb gradient required up to 2800FT. RWY16L/16R : 5.8% climb gradient required up to 1100FT. OBST ALT 399FT located at 1.2NM 138° FM end of RWY16L. OBST ALT 1470FT located at 6.2NM 182° FM end of RWY16L. OBST ALT 130FT located at 0.3NM 186° FM end of RWY16R.</p>		
<p>BERSA TRANSITION From YAMEK, to BERSA, to OMTA.</p> <p>GABAI TRANSITION From YAMEK, to SGE.</p>		

STANDARD DEPARTURE CHART - INSTRUMENT

RJFF / FUKUOKA

RNAV SID

KURUME FIVE DEPARTURE

RWY34R

Serial Number	Path Descriptor	Waypoint Identifier	Fly Over	Course °M(°T)	Magnetic Variation	Distance (NM)	Turn Direction	Altitude (FT)	Speed (KIAS)	Vertical Angle	Navigation Specification
001	VA	—	—	338 (330.4)	-8.0	—	—	+500	—	—	RNAV1
002	DF	FF401	—	—	-8.0	—	—	—	—	—	RNAV1
003	TF	FF402	—	068 (060.1)	-8.0	5.4	—	—	—	—	RNAV1
004	TF	FF403	—	158 (150.4)	-8.0	4.3	—	—	—	—	RNAV1
005	TF	YURRY	—	165 (157.2)	-8.0	13.1	—	—	—	—	RNAV1
006	TF	YAMEK	—	211 (202.7)	-8.0	5.7	—	—	—	—	RNAV1

RWY34L

Serial Number	Path Descriptor	Waypoint Identifier	Fly Over	Course °M(°T)	Magnetic Variation	Distance (NM)	Turn Direction	Altitude (FT)	Speed (KIAS)	Vertical Angle	Navigation Specification
001	VA	—	—	338 (330.4)	-8.0	—	—	+500	—	—	RNAV1
002	DF	F4L01	—	—	-8.0	—	—	—	—	—	RNAV1
003	TF	FF402	—	068 (060.1)	-8.0	5.5	—	—	—	—	RNAV1
004	TF	FF403	—	158 (150.4)	-8.0	4.3	—	—	—	—	RNAV1
005	TF	YURRY	—	165 (157.2)	-8.0	13.1	—	—	—	—	RNAV1
006	TF	YAMEK	—	211 (202.7)	-8.0	5.7	—	—	—	—	RNAV1

RWY16L/ RWY16R

Serial Number	Path Descriptor	Waypoint Identifier	Fly Over	Course °M(°T)	Magnetic Variation	Distance (NM)	Turn Direction	Altitude (FT)	Speed (KIAS)	Vertical Angle	Navigation Specification
001	VA	—	—	158 (150.3)	-8.0	—	—	+500	—	—	RNAV1
002	DF	YAMEK	—	—	-8.0	—	—	—	—	—	RNAV1

Waypoint Coordinates

Waypoint Identifier	Coordinates
F4L01	333928.0N / 1302356.2E
FF401	333931.4N / 1302403.3E
FF402	334212.3N / 1302939.7E
FF403	333827.6N / 1303213.2E
YURRY	332622.1N / 1303817.8E
YAMEK	332105.9N / 1303539.5E

STANDARD DEPARTURE CHART - INSTRUMENT

RJFF / FUKUOKA

RNAV TRANSITION

BERSA TRANSITION

Serial Number	Path Descriptor	Waypoint Identifier	Fly Over	Course °M(°T)	Magnetic Variation	Distance (NM)	Turn Direction	Altitude (FT)	Speed (KIAS)	Vertical Angle	Navigation Specification
001	IF	YAMEK	—	—	-8.0	—	—	—	—	—	RNAV1
002	TF	BERSA	—	210 (202.4)	-8.0	16.2	—	—	—	—	RNAV1
003	TF	OMUTA	—	210 (202.3)	-8.0	2.8	—	—	—	—	RNAV1

GABAI TRANSITION

Serial Number	Path Descriptor	Waypoint Identifier	Fly Over	Course °M(°T)	Magnetic Variation	Distance (NM)	Turn Direction	Altitude (FT)	Speed (KIAS)	Vertical Angle	Navigation Specification
001	IF	YAMEK	—	—	-8.0	—	—	—	—	—	RNAV1
002	TF	SGE	—	239 (231.2)	-8.0	19.4	—	—	—	—	RNAV1

Waypoint Coordinates

Waypoint Identifier	Coordinates
YAMEK	332105.9N / 1303539.5E
BERSA	330609.6N / 1302818.4E
OMUTA	330332.2N / 1302701.4E
SGE	330855.0N / 1301734.4E